

## ANSWERS TO REFEREE

COMMENT 1: The following sentence in the discussion:

“The worst results in terms of RMSE, MAE, and Std. were obtained for GALILEO constellation, probably because there aren’t as many satellites in the constellation as the GPS and GLONASS constellations have.” Can you back this statement up somehow? If not, I would suggest a word not as strong as ‘probably.’

Answer:

*We agree with the reviewer. As far as the authors know, this is the first work where observations of the constellation GALILEO are used for the determination of soil moisture, so there is no reference to support this conclusion. This assumption has been extrapolated based on the results obtained in GALILEO-only positioning compared to the GPS-only positioning results, which are always somewhat worse (Kiliszek et al. 2020, for example). In any case, the results presented in this manuscript are not so different from those obtained with the other two constellations, so that, following the reviewer's recommendations, the phrase has been modified to: “The least favorable results in terms of RMSE, MAE, and Std. were obtained for GALILEO constellation, one of the possible causes is that it does not have as many satellites in the constellation as the GPS and GLONASS constellations have”.*

*Finally, following the reviewer’s criteria, we decide to change also the word “probably” in the comparison between GPS and GLONASS constellation in the same paragraph of the paper.*

*Kiliszek, D., Araszkiwicz, A., Kroszczyński, K.: Accuracy of PPP along with the development of GPS, GLONASS and GALILEO. EGU General Assembly, 2020, Online, 4-8 May 2020, <https://doi.org/10.5194/egusphere-egu2020-7614>, 2020.*

COMMENT 2: I think authors misunderstood my point about the soil type and reference values. I was not referring to soil type affecting the linear relationship between soil moisture and phase, I was talking about soil type being an indicator of what the residual soil moisture content might be (Vresidual in the manuscript). The sentence in question (end of discussion, immediately before Conclusions) should be altered accordingly and probably moved to where Vresidual is discussed.

Answer:

*We are very sorry for the misunderstood, we have modified the text according to the reviewer's comments: the sentence has been slightly modified and have been situated in the same section, to where Vresidual is discussed.*

## FINAL REMARK

An Acknowledgements section is included in the final text:

*Acknowledgements.* The authors want to thank the Cajamar Centre of Experiences staff for all their help and collaboration during the field observation. The authors would also like to thank the comments from the editor and the two anonymous reviewers who have helped to improve the original manuscript.

# Multi-constellation GNSS interferometric reflectometry with mass-market sensors as a solution for soil moisture monitoring

Angel Martín<sup>1</sup>, Sara Ibáñez<sup>2</sup>, Carlos Baixauli<sup>3</sup>, Sara Blanc<sup>4</sup>, Ana B. Anquela<sup>1</sup>

<sup>1</sup>Department of Cartographic Engineering, Geodesy and Photogrammetry, Universitat Politècnica de Valencia, Valencia, 46022, Spain

<sup>2</sup>Centro Valenciano de Estudios sobre el Riego, Universitat Politècnica de Valencia, Valencia, 46022, Spain

<sup>3</sup>Centro de Experiencias Cajamar, Paiporta, Valencia, 46200, Spain

<sup>4</sup>Institute of Information and Communication Technologies, Universitat Politècnica de Valencia, Valencia, 46022, Spain.

*Correspondence to:* Angel Martín (aemartin@upvnet.upv.es)

10 **Abstract.** Per capita arable land is decreasing due to rapidly increasing population, and fresh water is becoming scarce and more expensive. Therefore, farmers should continue to use technology and innovative solutions to improve efficiency, save input costs, and optimise environmental resources (such as water). In the case study presented in this manuscript, the GNSS-IR technique was used to monitor soil moisture during 66 days, from December 3, 2018, to February 6, 2019, in the installations of the Cajamar Centre of Experiences, Paiporta, Valencia, Spain. Two main objectives were pursued. The first was the  
15 extension of the technique to a multi-constellation solution using GPS, GLONASS, and GALILEO satellites, and the second was to test whether mass-market sensors could be used for this technique. Both objectives were achieved. At the same time the GNSS observations were made, soil samples taken at 5 cm depth were used for soil moisture determination to establish a reference dataset. Based on a comparison with that reference data set, all GNSS solutions, including the three constellations and the two sensors (geodetic and mass-market), were highly correlated, with a correlation coefficient between 0.7 and 0.85.

## 20 1 Introduction

Soil moisture is a fundamental component of the hydrological cycle, and a key observable variable for optimising agricultural irrigation management. Additionally, soil moisture monitoring has been one of the main goals of the remote sensing satellite missions Soil Moisture and Ocean Salinity (SMOS), (Kerr et al., 2001), Soil Moisture Active Passive (SMAP), (Chan et al. 2016), and Sentinel-1, (Mattia et al., 2018). SMOS is used to derive global maps of soil moisture every three days at a spatial  
25 resolution of about 50 km, SMAP every two-three days with a spatial resolution of about 40 km (gridded to 36 km since the radiometer is the only instrument on board that works), and one Sentinel-1 satellite 12 days (two Sentinel-1 satellites are in orbit which decreases the revisit time) with a spatial resolution of about 1 km.

To obtain information about soil moisture at a very local scale and continuously, Global Navigation Satellite System (GNSS) reflectometry began to be tested as a possible solution (Masters et al., 2002; Zavorotny et al., 2003; Katzberg et al., 2005).

30 This was possible because GNSS satellites transmit in the L-band (microwave frequency), so the GNSS signal reflected by

nearby surfaces and recorded by the antenna contains information about the environment surrounding the antenna (scale of about 1000 m<sup>2</sup>). In particular, the ground-reflected global positioning system signal measured by a geodetic-quality GNSS system can be used to infer temporal changes in near-surface soil moisture. This technique, known as GNSS-interferometric reflectometry (GNSS-IR), analyses changes in the interference pattern of the direct and reflected signals, (Fig. 1), which are recorded in signal-to-noise ratio (SNR) data, as interferograms. Thus, GNSS-IR can be considered as another remote sensing technique for monitoring soil moisture in a local scale and continuously, independent from climatological conditions (the technique is valid in raining and foggy conditions) and illumination (day or night). Temporal fluctuations in the phase of the interferogram are indicative of changes in near-surface (depth of about 5-7 cm) volumetric soil moisture content, (Larson et al., 2008a, 2008b).

Commercially available geodetic-quality GNSS receivers and antennas can be used for GNSS-IR. The method has been tested with the Global Positioning System (GPS) satellite constellation, and it has been shown to provide consistent measurements of upper surface soil moisture content, (Larson et al., 2008a, 2008b, 2010; Larson and Nievinski, 2013; Chew et al., 2014, 2015, 2016; Small et al., 2015, Vey et al., 2015; Wan et al., 2015; Chen et al., 2016; Zhang et al., 2017).

With the use of the GPS constellation, the GPS-IR reflection footprint is far from homogeneous, Fig. 2, and some tracks cannot be included in the process and analysis (Vey et al., 2015; Chew et al., 2016). Therefore, GPS-IR needs to evolve to Global Navigation Satellite System reflectometry, GNSS-IR, where multi-constellation observation provides the solution. The integration of new navigation satellite constellations will produce a more homogeneous footprint around the antenna (Fig. 2). Roussel et al. (2016) introduced the GLONASS Russian constellation to retrieve soil moisture over bare soil, but there are no references in the literature for the European GALILEO or Chinese BEIDU constellations. Roesler and Larson (2018) provided a software tool for generating map GNSS-IR reflection zones that support GPS, GLONASS, GALILEO, and BEIDU constellations.

Therefore, the first novelty of this research was to extend, compare and combine the GPS-IR methodology to a multi-constellation scenario (GPS, GLONASS, and GALILEO; BEIDU is not introduced in this research because the antennas used in the experiment are not able to decode BEIDU signals), which will produce a much larger sample set of observations around the antenna than is obtained with only the GPS constellation, as shown in Fig. 2.

Additionally, geodetic-quality GNSS receivers and antennas are an expensive solution. If we keep in mind that the final market will be the agricultural market, a technique developed using those devices will never be introduced into the sector. Thus, the (main) second novelty of this research was the introduction of mass-market GNSS sensors as the basis for the technique. If the use of these mass-market devices can be confirmed, it will be possible to use them (one or several at the same time to add redundancies) at a very low cost.

## 2 Materials and methods

### 2.1 Location of the experiment

The experiment was conducted in the installations of the Cajamar Centre of Experiences, located in Paiporta, Valencia, Spain (39°25'3'' N, 0°25'4'' W), which is an agricultural research technology centre  
65 (<https://www.fundacioncajamarvalencia.es/es/comun/actividades/> in Spanish).

The centre began its activities in 1994. Some of the research topics carried out by the centre are the valorisation of agricultural by-products and the use of microorganisms in food, pharmaceuticals, and aesthetics using the latest biotechnology resources; the design of new containers and bio-functional formats for the marketing of healthy foods with high added value; improvement in irrigation automation, biological control management, and agronomic management in organic production; and the  
70 introduction of alternative value crops and new varieties that guarantee the sustainability of agricultural sector.

### 2.2 Instrumental and observations

A geodetic GNSS receiver (Trimble R10 GNSS receiver, from the Department of Cartographic Engineering Geodesy and Photogrammetry of the Universitat Politècnica de València) and a mass-market receiver (Navilock GNSS receiver based on a u-blox 8 UBX-M8030-KT chipset with a built-in antenna) connected to a Raspberry Pi 3 as a control device and for storing  
75 the observations, were used to obtain multi-constellation SNR observables (GPS, GLONASS and GALILEO). Five seconds sample rate observations were obtained simultaneously for both sensors (Fig. 3).

The radio-signal structure of GPS, GLONASS and GALILEO systems are similar. Different carrier signals in the L-band are broadcast, L1 and L2 corresponds with the two main frequencies of the signal emitted from the GPS satellites and E1 and E5 with the two main frequencies of the signal emitted from the GALILEO satellites. In contrast to GPS and GALILEO,  
80 GLONASS satellites transmit carrier signals at different frequencies from a basic L frequency, GLONASS L1 frequencies are:

$$f_{L1} = f_0 + k * \Delta f_{L1} \quad k = 1, 2, \dots, 24, \quad (1)$$

where  $f_0 = 1602.0 \text{ MHz}$ , and  $\Delta f_{L1} = 0.5625 \text{ MHz}$ , and  $k$  is the carrier number assigned to the specific GLONASS satellite  
85 (Hoffmann et al., 2008). Thus, the frequency for each satellite should be computed and included in the GLONASS file.

The frequencies used in the experiment were L1, for the GPS and GLONASS satellite constellations and E1 for the GALILEO constellation. This choice was forced because the mass-market device could not track the L2 or E5 satellite signals. However, Vey et al. (2011) showed that the soil moisture root mean square difference between L2C and L1 was only  $0.03 \text{ m}^3/\text{m}^3$ . L2C corresponds to the Civil L2 signal of the block satellites IIR-M and IIF of the GPS constellation, available only since 2005  
90 when the first block IIR-M was launched. This signal is designed specifically to meet commercial needs, which increases robustness of the signal, improve resistance to interference, and improve accuracy (Leick et al., 2015).

The GNSS-IR footprint for a single rising or setting satellite is an elongated ellipse in the direction of the satellite track (Fresnel ellipse or zones; Larson et al., 2010; Wan et al., 2015; Vey et al., 2015; Roesler and Larson, 2018). As the satellite rises and the elevation angle increases, the Fresnel zone becomes smaller and closer to the GNSS antenna. Data with elevation angles  
95 higher than 30 degrees should be discarded from the SNR series because they contain no significant oscillations and cannot be retrieved reliably. Data with elevation angles lower than 5 degrees should also be discarded in order to avoid strong multipath effects from trees, artificial surfaces, and structures surrounding the antenna. A GNSS satellite takes about one hour to rise from an elevation angle of 5 degrees to an angle of 30 degrees.

The geodetic GNSS receiver store the observations (including SNR data) in the commonly used RINEX files, so the elevation  
100 and azimuth of a satellite for an epoch should be computed from the observation RINEX file and the navigation RINEX file, (Hofmann-Wellenhof et al., 2008).

The mass-market receiver uses NMEA GSV sentences to provide integer numbers for elevation, azimuth and signal-to-noise ratio (SNR) directly. NMEA is an acronym for the National Marine Electronics Association. GNSS NMEA is a standard data format supported by all manufacturers to output measurement data from a sensor in a pre-defined format in ASCII. In the case  
105 of GNSS, it output position, velocity, time and satellite related data (for the constellations that the antenna can decode). There are quite a few NMEA messages or sentences, specifically, GSV sentences provide integer numbers for elevation, azimuth and signal-to-noise ratio.

The results were compared with soil moisture measurements based on soil samples taken at a depth of 5 cm and weighed before and after being dried (gravimetric method) in a laboratory (Fig. 4). These measurements were considered the reference  
110 dataset. The soil samples were taken one per day except weekends and the location, in comparison with the antenna position, can be seen in Fig. 2.

In total, 66 days of measurements, from December 3, 2018, to February 6, 2019, were observed, processed, and analysed. The height of the antennas from the ground was 1.80 m for the geodetic GNSS device and 1.84 m for the mass-market device.

Precipitation data were added in the final plot results. These data were obtained from a meteorological station located in the  
115 Cajamar Experiences Centre (100 meters from the GNSS antennas).

### 2.3 Theoretical background

The theoretical background is based on the procedure developed by Larson et al., (2010) and detailed in Chew et al., (2014), vey et al., (2015), and Zhang et al., (2017). Each valid track of a satellite should be separated into ascending path and descending path.

120 The processing of each satellite track can be summarised as follows:

- 1) SNR data are converted from dB units to linear scale in volts using the conversion equation (S stands for SNR in the next equation and for the rest of equations in the manuscript)  $S_{linear} = 10^{S/20}$  (vey et al., 2016).
- 2) A low-order polynomial (second degree) is fit to the  $S_{linear}$  in order to eliminate the direct satellite signal, so that the reflected signal is isolated:  $S_{linear}^{reflected}$ , (Wan et al., 2015; Chew et al., 2016).

- 125 3) A Lomb-Scargle periodogram (Lomb, 1976; Press et al., 1992; Roesler and Larson, 2018), is then computed from  $S_{lineal}^{reflected}$ , and the track goes to the next step only if there is a clear signal that reflects a primary wave. Tracks with multiple peaks or low maximum average power (less than four times the background noise) are not included in the next step. If the Lomb-Scargle periodogram is computed using the sine elevation angle as the input X axis, the result converts the frequency into antenna height in the output X axis. Only tracks with computed antenna height consistent with the measured antenna height (less than 0.1 meters difference), go to the next step.
- 130 4) The selected tracks are modelled using the expression below:

$$S_{lineal}^{reflected} = A \cos\left(\frac{4\pi h}{\lambda} \sin e + \phi\right) \quad (2)$$

- 135 The equation means that  $S_{lineal}^{reflected}$  can be modelled in terms of the amplitude  $A$  and phase offset  $\phi$  of a primary wave.  $\lambda$  is the GNSS wavelength (L1 for GPS and GLONASS and E1 for GALILEO),  $e$  is the satellite elevation, and  $h$  is the antenna height, which is assumed to be a constant due to the low signal penetration on the ground (Chew et al., 2014; Roussel et al., 2016; Zhang et al., 2017). The least squares algorithm (Strang and Borre, 1997; Leick et al., 2015) is used to estimate  $A$  and  $\phi$ .
- 140 5) Chew et al., (2013) derived a linear relationship between the previously computed phase offset and soil moisture with a slope of  $65.1^\circ$  in order to obtain the GNSS-derived volumetric water content,  $VW_{GNSS}$  ( $m^3/m^3$ ).  $V$  stands for  $VW_{GNSS}$  in the next equation and for the rest of the manuscript:

$$V_{GNSS} = \frac{\Delta\phi_t}{65.1} + V_{Residual} \quad (3)$$

- 145 However, this value should be computed using the reference values in order to convert the satellite tracks phase values into GNSS-derived volumetric water content, because this linear relationship can be positive or negative. Zhang et al. (2017) showed the importance of this adjustment with the test data in order to obtain better results (their results showed a decrease of the final standard deviation from  $0.036 m^3m^{-3}$  -using the linear relationship of  $65.1^\circ$ - to  $0.008 m^3m^{-3}$  -using the adjusted linear relationship-).
- 150  $V_{Residual}$  in Equation 3, is the minimum soil moisture observation from the reference data set (obtained from the soil samples). This minimum value should be taken from the reference observations as long as the GNSS observation is continuous and without interruptions. In the case that there is any interruption in the GNSS observation data, this value must be chosen again among the reference values after the interruption.  $\Delta\phi_t = \phi - \phi_o$  is calculated with respect to a reference phase  $\phi_o$  computed in this work as proposed by Chew et al. (2016): the mean of the lowest 15%

of the computed phases for each satellite tracks during the retrieval period.  $\phi_o$  should be computed again in the case of interruption of the GNSS signal. Ascending and descending paths for the same satellite are treated separately.

- 6) Finally, the mean  $V$  value of all satellite tracks of the same constellation that pass at different times during the day is computed, so the final GNSS soil moisture represents a temporal average for all observations analyzed during one day. To address the objectives of this research, we have three different results, one for each GNSS constellation.

160

### 3 Results

#### 3.1 Processing

RINEX observation and navigation files from the geodetic GNSS antenna were used to generate the input file for the processing process. This file contained year, month, day, hour, satellite identification, SNR, elevation, and azimuth for every observed epoch. We computed three different files (GPS, GALILEO and GLONASS). The frequency for each GLONASS satellite should be also computed and included in the GLONASS file.

165

The file containing the NMEA observations from the mass-market antenna was used to generate three different input files for the processing process, one for each satellite constellation. However, due to the integer nature of the SNR, elevation, and azimuth observation numbers, an extra processing step was included for the mass-market observation files. This step used the navigation files from the International GNSS Service (IGS) repository (<http://www.igs.org>) to compute float numbers for elevation and azimuth values of the observed satellites.

170

The rest of the processing followed the steps defined in the previous section. Only full GNSS tracks data covering more than 30 minutes and cover more than 10 degrees of elevation in its trajectory were considered in our study.

#### 3.2 Results

The geodetic antenna SNR data in volts for satellite GPS number 23 are shown in Fig. 5a, the SNR data with the direct signal removed are shown in Fig. 5b, the Lomb-Scargle periodogram for the SNR reflected signal is shown in Fig. 5c, and the SNR reflected signal with the adjusted wave (Step 4 in the previous section) is shown in Fig. 5d. Fig. 6 portrays the same concepts for the same satellite but using the mass-market antenna observations. Fig. 7 and 8 portray the same concepts for the GLONASS satellite number 5, and Fig. 9 and 10 display these for the GALILEO satellite number 21.

175

The SNR values from the geodetic antenna and the mass-market antenna for the GPS constellation are similar, as suggested in Li and Geng (2019), because the u-blox chipset uses an active, right-handed, circularly polarized antenna with uniform antenna gain. However, the SNR values for GLONASS and GALILEO present a systematic bias of about 3-5 db-Hz between the geodetic and mass-market antennas (Fig. 7a and 8a and Fig. 9a and 10a).

180

A linear relationship between reference data and every GNSS constellation and antenna was computed using the methodology proposed by Zhang et al. (2017), the results can be seen in Table 1. Based on the positive values for all lineal relationships and

185



the conclusions on Zhang et al. (2017), a slope of  $65.1^\circ$  between the all GNSS computed phase offset and the soil moisture was used to homogenize the results among different constellations and the two different antennas.

However, two different values for  $V_{Residual}$  and  $\theta_0$  were used due to an outage of the electrical power during three days (from day 40 to day 42 of the experiment), where no observations were recorded.

190 The results presented the average value of soil moisture around the geodetic and mass-market antennas per day, obtained from all valid GNSS tracks of all satellites per constellation or using the three constellations.

Fig. 11, 12, and 13 show a comparison of the daily soil moisture from GPS, GLONASS, and GALILEO, respectively, where the results of the geodetic and mass-market antennas can be compared with the reference gravimetric data set. Daily precipitation amounts are also included in the figures.

195 Finally, Fig. 14 show the combined solution of the three constellations as an average of the results of the individual solutions, which can be considered as a combined multi-constellation solution.

The numerical values for Fig. 11, 12, 13 and 14 are listed in Table 2, where MAE is the mean absolute error, RMSE is the root mean square error, mean and Std. are the mean and the standard deviation respectively between the GNSS antennas and the reference values. The Pearson correlation coefficient can be used to summarize the strength of the linear relationship between  
200 two data samples. Spearman correlation can be used to summarize if two variables are related by a nonlinear relationship, such that the relationship is stronger or weaker across the distribution of the variables.

#### 4 Discussion

Based in the results summarized in Table 2, equivalent results between geodetic and mass-market antenna is obtained for RMSE, MAE, Mean and Std., showing the good performance of the mass-market antenna. Pearson and Spearman correlation  
205 are equivalent between Geodesic and Mass-market antenna for every constellation and comparing the constellations. These confirms that a lineal relationship can be considered between the soil moisture results obtained from all GNSS antennas and the sample observations.

The **least favorable** results in terms of RMSE, MAE and Std. were obtained for GALILEO constellation, **one of the possible causes is that it does not have** as many satellites in the constellation as the GPS and GLONASS constellations have. GLONASS  
210 constellation offers slight improvement in terms of RMSE, MAE and Std. results in comparison with GPS, GLONASS range of values appears more compressed for both the geodetic and mass-market antennas, **one of the possible causes is that** GPS constellation, in the moment of the observations, had three different satellite blocks (blocks IIR, IIF and IIF) with different capabilities, and GLONASS only two (blocks M and K). However, the ranges of RMSE, MAE and Std. considering GPS, GLONASS and GALILEO constellations (both geodetic and mass-market antennas) are less than 0.01 m<sup>3</sup>/m<sup>3</sup> and less than  
215 0.15 for Pearson or Spearman correlation, so we can consider that the three constellations produce similar  $V_{GNSS}$  values, regardless of the type of antenna used, opening the possibility of using the three constellations in combination as a multi-constellation solution. The last two columns of Table 2 show the statistical summary of the constellations combination for both

Eliminado: worst

Eliminado: probably because

Eliminado: there aren't

Eliminado: probably

Eliminado: because

the geodetic and the mass-market antenna, where it can be seen that the values obtained are equivalent to those of the previous columns.

225 Our RMS results using the a priori slope values of  $65.1^\circ$  are comparable with those obtained by Zhang et al. (2017), who processed six months of continuous observations and obtained a mean standard deviation value of  $0.036 \text{ m}^3/\text{m}^3$ , and those of Vey et al. (2015), who processed 6 years of observations and obtained a standard deviation value of  $0.06 \text{ m}^3/\text{m}^3$ .

The SNR bias between the geodetic and mass-market antenna for GLONASS and GALILEO constellations (Fig.7b and 8b and Fig. 9b and 10b) has no effects in the final phase offset variations for the adjusted wave.

230 According to Step 3 of Section 2.3, the 70% of the GPS tracks recorded by the geodetic antenna were considered valid for processing, as were 73% for GALILEO, and 74% for GLONASS. This percentage is reduced to around a 10% if we consider the tracks recorded by the mass-market antenna. Nonetheless, one of the main important problems in this research is related with the selection of the correct tracks to be processed and adjusted using Step 4 of Section 2.3. Based on the mentioned criteria (tracks with multiple peaks or low maximum average power and computed reflector height consistent with the measured  
235 antenna height), some tracks that should not be processed are finally processed (around 8% of all tracks irrespective the constellation). These wrongly processed tracks introduce outliers in the computed  $V_{GNSS}$ , which are eliminated in the daily final mean  $V_{GNSS}$  computation because they produce a high RMS in the daily computations using all satellites. One way to accomplish this task could be to use good figures, such as those from Fig. 5c Fig. 5d, to produce a valid set of training images and use machine learning tools (image recognition) to decide automatically whether a new track can be considered as a good  
240 track (so it can be processed) or not. This idea is currently under development.

In situ observations are needed to solve Eq. 3 ( $V_{Residual}$  parameter). However, if there are no reference values, this constant cannot be included, and the results will present an offset in comparison with the real values. A possible solution would be the estimation of the parameter based on the soil type (URL 1): though, that requires having a long enough time series to make the assumption that, at some point during the time series, soil moisture was low enough to hit the residual value. However, the

245 results can be used in a relative way, that is, can be used to infer VWC variations from one day to another. This relative comparison can be performed only if the observations are continuous. If there is an interruption in the raw data (because the antenna is turned off) of more than two or three hours, the previous reference is lost and the relative comparisons should start again (from the moment the antenna is turned on again). In situ observations are also needed if we want to adjust the linear relationship between the computed phase offset and the soil moisture, as is developed in Zhang et al. (2017); however, in case  
250 the linear relationship is positive, a value of  $65.1^\circ$  can also be used to obtain acceptable results.

**Eliminado:** if there are no reference values, they can be estimated based on the soil type (URL 1). Though, that requires having a long enough time series to make the assumption that, at some point during the time series, soil moisture was low enough to hit the residual value. However,

## 5 Conclusions

The case study presented in this research is focused on the GNSS SNR data acquisition and processing using the GNSS-IR technique to monitor soil moisture. The main objectives of this research were the use, comparison and combination of GPS,

GLONASS, and GALILEO constellations solutions and the use and comparison of a geodetic and mass-market antenna solutions.

260 Independent GPS, GLONASS, and GALILEO solutions were generated to demonstrate that the technique can be extended to a multi-constellation solution. This is necessary because a single constellation solution presents a reflection footprint that is far from homogeneous around the antenna and because 30-35% of the observed satellite tracks of the geodetic antenna are not valid for processing (40-45% if the mass-market antenna is considered).

265 The use of a mass-market GNSS antenna was confirmed to be a viable tool for GNSS-IR, with the caution of using the IGS navigation files to transform the observed integer numbers obtained in the NMEA messages for the elevation and azimuth of the satellites into floating numbers. With the use of mass-market sensors, it will become possible to design scenarios with several GNSS stations generating redundant observations. Therefore, maps of soil moisture variations by specific and selective areas of soil, cultivation, and/or management can be generated, instead of obtaining only an average value for the entire observation area.

270 GNSS-IR is still a technique with numerous technological challenges in order to becoming a competitive solution with respect to current observation techniques, but it has great potential with regard to continuity of observation (can be implemented in a real or quasi-real time scenario), precision, and measurement acquisition cost if mass-market antennas are used.

275 Acknowledgements. The authors want to thank the Cajamar Centre of Experiences staff for all their help and collaboration during the field observation. The authors would also like to thank the comments from the editor and the two anonymous reviewers who have helped to improve the original manuscript.

Con formato: Color de fuente: Texto 1

#### Data availability

GNSS raw observations used to conduct this study are available upon request from the corresponding author (Angel Martin)

#### 280 Author contribution

Angel Martín, Sara Ibáñez and Carlos Baixauli designed the experiment, Angel Martín, Ana B. Anquela and Sara Blanc designed and collected GNSS observations, Carlos Baixauli and Sara Ibáñez collected and process the soil samples, Angel

Con formato: Interlineado: 1.5 líneas

Martín and Sara Blanc Wrote all the software libraries in Python, Angel Martín and Ana B. Anquela conducted the analysis of the results, Angel Martín wrote the manuscript.

## 285 **Competing interests**

The authors declare that they have no conflict of interest.

## **References**

- Chan, S. K., Bindlish, R., O'Neill, P. E., Njoku, E., Jackson, T., Colliander, A., Chen, F., Burgin, M., Dunbar, S., Piep-meier, J., Yueh, S., Entekhabi, D., Cosh, M. H., Caldwell, T., Walker, J., Wu, X., Berg, A., Rowlandson, T., Pacheco, A., McNairn, H., Thibeault, M., Martínez-Fernández, J., González-Zamora, A., Seyfried, M., Bosch, D., Starks, P., Goodrich, D., Prueger, J., Palecki, M., Small, E. E., Zreda, M., Calvet, J.-C., Crow, W., and Kerr, Y.: Assessment of the SMAP passive soil moisture product, *IEEE T. Geosci. Rem. Sens.*, 54, 4994–5007, 2016.
- Chen, Q., Won, D., Akos, D.M., and Small, E.E.: Vegetation using GPS interferometric reflectometry: experimental results with a horizontal polarized antenna, *IEEE J. Select. Top. Appl. Earth Obs. Rem. Sens.*, 9(10), 4771-4780, 2016.
- 295 Chew, C.C., Small, E.E., Larson, and K.M., Zavorotny, V.U.: Effects of near-surface soil moisture on GPS SNR data: development and retrieval algorithm for soil moisture, *IEEE T. Geosci. Rem. Sens.*, 52(1), 537-543, 2014.
- Chew, C.C., Small, E.E., Larson, K.M., and Zavorotny, U.Z.: Vegetation sensing using GPS-interferometric reflectometry: theoretical effects of canopy parameters on signal-to-noise ratio data, *IEEE T. Geosci. Rem. Sens.*, 53(5), 2755-2764, 2015.
- Chew, C.C., Small, E.E., and Larson, K.M.: An algorithm for soil moisture estimation using GPS-interferometric reflectometry for bare and vegetated soil, *GPS Solut.*, 20(3), 525-537, 2016.
- 300 Hofmann-Wellehof, B., Lichtenegger, H., and Wasle, E.: GNSS Global Navigation Satellite Systems, GPS, GLONASS, GALILEO and more, Ed. SpringerWienNewYork 2008.
- Katzberg, S.J., Torres, O., Grant, M.S., and Masters, D.: Utilizing calibrated GPS reflected signals to estimate soil reflectivity and dielectric constant: results from SMEX02, *Rem. Sens. Environ.*, 100(1), 17-28, 2005.
- 305 Kerr, Y., Waldteufel, P., Wigneron, J., Martinuzzi, J., Font, J., and Berger, M.: Soil moisture retrieval from space: The Soil Moisture and Ocean Salinity (SMOS) mission, *IEEE T. Geosc. Rem. Sens.*, 39, 1729-1735, 2001.
- Larson, K.M., Small, E.E., Gutmann, E. D., Bilich, A.L., Axelrad, A., and Braun, J.J.: Using GPS multipath to measure soil moisture fluctuations: initial results, *GPS solut.*, 12(3), 173-177, 2008a.
- Larson, K.M., Small, E.E., Gutmann, E. D., Bilich, A.L., Braun, J.J., and Zavorotny, V.U.: Use of GPS receivers as a soil moisture network for water cycle studies, *Geophys. Res. Lett.*, 35, L24405, 2008b.
- 310 Larson, K.M., Braun, J.J., Small, E.E., and Zavorotny, V.U.: GPS multipath and its relation to near-surface soil moisture content, *IEEE J. Selec. Top. Appl. Earth Obs. Rem. Sens.*, 3(1), 91-99, 2010.

Eliminado: ¶

- 315 Larson, K.M., and Nievinski, F.G.: GPS snow sensing: results from the EarthScope plate boundary observatory, *GPS solut.*, 17(1), 41-52, 2013.
- Leick, A., Rapoport, L., and Tatarnikov, D.: *GPS satellite surveying*. John Wiley & Sons, fourth edition, 840 pp. 2015.
- Li, G., Geng, J. (2019): Characteristics of raw multi-GNSS measurement error from Google Android smart devices, *GPS Solut.*, 23(3), <https://doi.org/10.1007/s10291-019-0885-4>, 2015.
- 320 Lomb, N.R.: Least-squares frequency-Analysis of unequally spaced data, *Astrophys. Space Sci.* 39(2), 447-462, 1976.
- Masters, D., Axelrad, P., and Katzberg, S.: Initial results of land-reflected GPS bistatic radar measurements in SMEX02, *Rem. Sen. Environ.*, 92(4), 507-520, 2002.
- Mattia, F., Balenzano, A., Satalino, G., Lovergine, F., Peng, J., Wegmuller, U., Cartus, O., Davidson, M.W.J., Kim S., Johnson, J., Walker, J., Wu, X., Pauwels, V.R.N., McNairn, H., Caldwell, T., Cosh, M., and Jackson, T: Sentinel-1 & Sentinel-2 for
- 325 SOIL Moisture Retrieval at Field Scale, IGARSS 2018-2018 IEEE I. Geos. Rem. Sens. Symposium, <https://doi.org/10.1109/IGARSS.2018.8518170.6147-6150>, 2018.
- Press, W.H., Teukolsky, S.S., Vetterling, W.T., and Flannery, B.P.: *Numerical recipes in Fortran 77*, vol. 1, 2nd edn. Cambridge University Press, New York, pp 569-573, 1992.
- Roesler, C., and Larson, K.M.: Software tools for GNSS interferometric reflectometry (GNSS-IR), *GPS Solut.*, 22: 80.
- 330 <https://doi.org/10.1007/s10291-018-0744-8>, 2018.
- Roussel, N., Frappart, F., Ramillien, G., Darroes, J., Baup, F., Lestarquit, L., and Ha, M.C.: Detection of soil moisture variations using GPS and GLONASS SNR data for elevation angles ranging from 2° to 70°, *IEEE J. Selec. Top. Appl. Earth Obs. Rem. Sens.*, 9(10), 4781-4794, 2016.
- Small, E.E., Larson, K.M., Chew, C.C., Dong, J., and Ochsner, T.E.: Validation of GPS-IR soil moisture retrievals: comparison
- 335 of different algorithms to remove vegetation effects, *IEEE J. Selec. Top. Appl. Earth Obs. Rem. Sens.*, 9(10), 4759-4770, 2016.
- Strang, G., and Borre, K.: *Linear algebra, Geodesy and GPS*. Wellesley-Cambridge Press, 624 p, 1997.
- URL 1: <https://www.unavco.org/data/gps-gnss/derived-products/pbo-h2o/documentation/documentation.html#soil>. Accessed on December 2019.
- Vey, S., Güntner, A., Wickert, J., Blume, T., and Ramatschi, M.: Long-term soil moisture dynamics derived from GNSS
- 340 interferometric reflectometry: a case study for Sutherland, South Africa. *GPS Solut.*, DOI 10.1007/s10291-015- 0474-0, 2015.
- Wan, W., Larson, K.M., Small, E.E., Chew, C.C., and Braun, J.J.: Using geodetic GPS receivers to measure vegetation water content, *GPS solute.*, 19, 237-248, 2015.
- Zavorotny, V.U., Masters, D., Gasiewski, A., Bartram, B., Katzberg, S., Aselrad, P., and Zamora, R.: Seasonal polarimetric measurements of soil moisture using tower-based GPS bistatic radar, In: *Proceedings of IEEE 2003 I. geos. Rem. Sens. symposium, IGARSS 2003*, vol. 2, 781-783, 2003.
- 345 Zhang, S., Roussel, N., Boniface, K., Ha, M. C., Frappart, F., Darrozes, J., Baup, F., and Calvet, J.C.: Use of reflected GNSS SNR data to retrieve either soil moisture or vegetation height from a wheat crop, *Hydrol. Earth Syst. Sci.*, 21, 4767-4784, 2017.

350

Eliminado: 1

	Geodetic antenna	Mass-market antenna
GPS constellation	157.97	330.50
GALILEO constellation	60.97	144.93
GLONASS constellation	22.18	33.33

**Table 1.** Linear relationship (in degrees) between GNSS observations and reference soil moisture observations.

355

	GPS vs. in situ		GALILEO vs. in situ		GLONASS vs. in situ		GNSS vs. in situ	
	Geodetic	Mass-market	Geodetic	Mass-market	Geodetic	Mass-market	Geodetic	Mass-market
RMSE (m <sup>3</sup> /m <sup>3</sup> )	0.025	0.026	0.028	0.024	0.020	0.020	0.022	0.022
Pearson correlation	0.77	0.72	0.75	0.76	0.83	0.84	0.80	0.81
Spearman correlation	0.78	0.75	0.80	0.80	0.82	0.85	0.78	0.81
MAE (m <sup>3</sup> /m <sup>3</sup> )	0.020	0.021	0.023	0.020	0.016	0.016	0.017	0.018
Mean (m <sup>3</sup> /m <sup>3</sup> )	0.002	-0.003	-0.001	0.005	0.000	0.002	0.001	0.001
Std (m <sup>3</sup> /m <sup>3</sup> )	0.025	0.026	0.028	0.023	0.020	0.020	0.022	0.022

**Table 2.** Statistical summary of the soil moisture estimates from the GPS, GALILEO and GLONASS constellations with the reference (in situ) values. GNSS is the combination of the three constellations. RMSE is the root mean square error, MAE is the mean absolute error and Std. is the standard deviation of the differences.

365

Figures

380






Figure 1. Principle of Global Navigation Satellite System interferometric reflectometry (GNSS-IR).  $H_0$  is the antenna height, and  $\theta$  is the satellite elevation angle.

385

390

395





400 Figure 2. GNSS Fresnel ellipses around the geodetic antenna during one of the observation days. GPS constellations satellites are shown in black, GLONASS satellites are shown in red, and GALILEO satellites are shown in blue. Green circle is the location where soil samples have been taken.

405

410

415

420



425

430

435

440



**Figure 3.** Instrumental configuration in the field campaign. A geodetic-quality GNSS antenna and a mass-market GNSS antenna were working at the same time.

445

450

455

460

465

470

475

480




Figure 4. Gravimetry method used for producing a reference dataset. Step 1: taking the soil sample. Steps 2 and 4: weighing the sample. Step 3: drying the sample.

485

490

495




Figure 5. GPS satellite number 23 observed with the geodetic antenna. a) SNR data in volts, b) SNR data with the direct signal removed, c) Lomb-Scargle periodogram for the SNR reflected signal, d) SNR reflected signal with the adjusted wave.

520

525


530

535

540

545

550



555 Figure 6. GPS satellite number 23 observed with the mass-market antenna. a) SNR data in volts, b) SNR data with the direct signal removed, c) Lomb-Scargle periodogram for the SNR reflected signal, d) SNR reflected signal with the adjusted wave.

560

565

570

575

580

585

590





Figure 7. GLONASS satellite number 5 observed with the geodetic antenna. a) SNR data in volts, b) SNR data with the direct signal removed, c) Lomb-Scargle periodogram for the SNR reflected signal, d) SNR reflected signal with the adjusted wave.

595

600

605

610



630 Figure 8. GLONASS satellite number 5 observed with the mass-market antenna. a) SNR data in volts, b) SNR data with the direct  
 635 signal removed, c) Lomb-Scargle periodogram for the SNR reflected signal, d) SNR reflected signal with the adjusted wave.



635

640


645

650


655



660



665



670 **Figure 9. GALILEO satellite number 21 observed with the geodetic antenna. a) SNR data in volts, b) SNR data with the direct signal removed, c) Lomb-Scargle periodogram for the SNR reflected signal, d) SNR reflected signal with the adjusted wave.**

675

680

685

690

695

700

705





Figure 10. GALILEO satellite number 21 observed with the mass-market antenna. a) SNR data in volts, b) SNR data with the direct signal removed, c) Lomb-Scargle periodogram for the SNR reflected signal, d) SNR reflected signal with the adjusted wave.

710

715

720






725

Figure 11. GPS comparison of daily soil moisture. The results of the geodetic and mass-market antennas are compared with the reference gravimetric data set.

730

735

740




745

Figure 12. GLONASS comparison of daily soil moisture. The results of the geodetic and mass-market antennas are compared with the reference gravimetric data set.

750

755

760



765 Figure 13. GALILEO comparison of daily soil moisture. The results of the geodetic and mass-market antennas are compared with the reference gravimetric data set.

770

775

780




Figure 14. Multi-constellations GNSS (GPS+GLONASS+GALILEO combination) comparison of daily soil moisture. The results of the geodetic and mass-market antennas are compared with the reference gravimetric data set.